



CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant



Features

- Up to 50Gbps data rate per channel by PAM4 modulation
- 4 duplex channels transmitters and receivers
- Integrated CWDM LD and PD array
- LC/UPC connecting interface compliant
- Single +3.3V power supply
- DDM function implemented
- Hot-pluggable QSFP56 form factor
- Transmission length up to 2km
- Low power dissipation:<6.5w
- International class 1 laser safety certified
- Operating temperature range: 0°C ~ +70 °C
- Compliant with ROHS10

Applications

- 200GBASE-FR4 Ethernet
- Switch & Router Connections
- Data Centers
- Other 200G Interconnect Requirements

Standards

- IEEE 802.3cd
- CMIS Rev 4.0
- OIF-CEI-04.0 56G-VSR-PAM4
- IEEE 802.3bs Annex120E
- SFF-8024 Rev. 4.6
- SFF-8679 Rev1.8
- SFF-8665 Rev1.9

PART NUMBER	Monitor	INPUT/OUTPUT	SIGNAL DETECT	TEMPERATURE
CL-QSFP56-LR4-200G	X	AC/AC	TTL	0°C to 70 °C
CL-QSFP56-LR4-200Gi	X	AC/AC	TTL	-40°C to 85 °C



CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant


Absolute Maximum Ratings

Parameter	Symbol	Min.	Max.	Unit	Notes
Storage Temperature	T _s	-40	85	°C	
Supply Voltage	V _{CC}	-0.5	4.0	V	
Relative Humidity (non-condensing)	RH	5	85	%	


Recommended Operating Conditions

Parameter	Symbol	Min.	Typical	Max.	Unit	Notes
Operating Case Temperature	T _{OPR}	0	-	70	°C	
Power Supply Voltage	V _{CC}	3.135	3.3	3.465	V	
Baud Rate (Per Channel)	BR		26.5625		GBd	

Optical Interface



Principle diagram





CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant

Functional Characteristics (Optical)

The following tables list the performance specifications for the various functional blocks of the integrated optical transceiver module.

Transmitter&Receiver Optical Specifications

Parameter	Symbol	Unit	Min	Typ	Max	Notes
Transmitter (per Lane)						
Signaling Speed per Lane		GBd		26.5625		
Modulation format				PAM4		
Center wavelength	WL	nm	1264.5	1271	1277.5	
			1284.5	1291	1297.5	
			1304.5	1311	1317.5	
			1324.5	1331	1337.5	
Side-mode suppression ratio	SMSR	dB	30			
Average Launch Power per Lane	TXPx	dBm	-4.2		4.7	
Tx OMA per lane	TxOMA	dBm	-1.2		4.5	
Optical Extinction Ratio	ER	dB	3.5			
Transmitter and dispersion eye closure for PAM4 per Lane	TDEC Q	dB			3.3	
Optical return loss tolerance	ORL	dB			16.5	
Relative Intensity Noise	RIN	dB/Hz			-132	
Receiver(per lane)						
Signaling Speed per Lane				26.5625		
Center wavelength	WL	nm	1264.5	1271	1277.5	
			1284.5	1291	1297.5	
			1304.5	1311	1317.5	
			1324.5	1331	1337.5	
Damage Threshold	DT	dBm	5.7			
Average Receive Power per Lane	RXP	dBm	-8.2		4.7	
Receiver reflectance	Rfl	dB			-26	



CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant

Difference in receive power between any two lanes		dB			4.1	
Receiver sensitivity (OMAouter)		dBm			-6	
Stressed receiver sensitivity (OMAouter)		dBm			-3.6	

Functional Characteristics (Electrical)

Electrical Specification


Parameter	Symbol	Unit	Min	Typ	Max	Notes
Supply Voltage	VCC VCC3.3-Tx VCC3.3-Rx	V	3.135	3.3	3.465	
Power Consumption	Pc	W			6.5	
Transceiver Power-on Initialize Time		ms			2000	
Transmitter						
Differential peak-to-peak input voltage tolerance		mV	900			
Differential termination mismatch		%			10	
Differential input return loss(SDD11)		dB			See CEI-56G -VSR	
Common-mode to differential conversion and differential to common-mode conversion(SCD11,SDC11)		dB			See CEI-56G -VSR	
Receiver						
Differential peak-to-peak output voltage		mV			900	
DC Common Mode Voltage	Vcm	mV	-0.35		2.85	
AC Common Mode Noise, RMS		mV			17.5	
Differential termination mismatch		%			10	
Differential output return loss(SDD22)		dB			See CEI-56G -VSR	



CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant

Common-mode to differential conversion and differential to common-mode conversion(SCD22,SDC22)		dB			See CEI-56G -VSR	
IIC communication						
IIC Clock frequency	-	KHZ	/	400	1000	
clock stretching	-	us	/	/	500	
Data hold time	-	ns	/	/	/	

Pin Definitions



PIN	Logic	Symbol	DESCRIPTION	NOTE
1		GND	Ground	1
2	CML-I	Tx2n	Transmitter Inverted Data Input	
3	CML-I	Tx2p	Transmitter Non-Inverted Data output	
4		GND	Ground	1
5	CML-I	Tx4n	Transmitter Inverted Data Input	



CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant

6	CML-I	Tx4p	Transmitter Non-Inverted Data output	
7		GND	Ground	1
8	LVTTL-I	ModSelL	Module Select	
9	LVTTL-I	ResetL	Module Reset	
10		VccRx	+3.3V Power Supply Receiver	2
11	LVCOMS-I/O	SCL	2-Wire Serial Interface Clock	
12	LVCOMS-I/O	SDA	2-Wire Serial Interface Data	
13		GND	Ground	1
14	CML-0	Rx3p	Receiver Non-Inverted Data Output	
15	CML-0	Rx3n	Receiver Inverted Data Output	
16		GND	Ground	1
17	CML-0	Rx1p	Receiver Non-Inverted Data Output	
18	CML-0	Rx1n	Receiver Inverted Data Output	
19		GND	Ground	1
20		GND	Ground	1
21	CML-0	Rx2n	Receiver Inverted Data Output	
22	CML-0	Rx2p	Receiver Non-Inverted Data Output	
23		GND	Ground	1
24	CML-0	Rx4n	Receiver Inverted Data Output	
25	CML-0	Rx4p	Receiver Non-Inverted Data Output	
26		GND	Ground	1
27	LVTTL-0	ModPrsL	Module Present	
28	LVTTL-0	IntL/RxLOSL	Interrupt. Optionally configurable as RxLOSL via the management interface (SFF-8636)	
29		VccTx	+3.3 V Power Supply transmitter	2
30		Vcc1	+3.3 V Power Supply	2
31	LVTTL-I	LPMoDe/TxDis	Low Power Mode. Optionally configurable as TxDis via the management interface (SFF-8636).	
32		GND	Ground	1
33	CML-I	Tx3p	Transmitter Inverted Data Input	




CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant

34	CML-I	Tx3n	Transmitter Non-Inverted Data output	
35		GND	Ground	1
36	CML-I	Tx1p	Transmitter Inverted Data Input	
37	CML-I	Tx1n	Transmitter Non-Inverted Data output	
38		GND	Ground	1

Notes:


1. GND is the symbol for signal and supply (power) common for the QSFP56 module. All are common within the module and all module voltages are referenced to this potential unless otherwise noted. Connect these directly to the host board signal common ground plane.
2. VccRx, Vcc1 and VccTx are the receiving and transmission power suppliers and shall be applied concurrently. Recommended host board power supply filtering is shown in Figure 3 below. Vcc Rx, Vcc1 and Vcc Tx may be internally connected within the module in any combination.

Module Memory Map






CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant



Host Board Power Supply Filtering


Any voltage drop across a filter network on the host is counted against the host DC set point accuracy specification. Inductors with DC resistance of less than 0.1 Ω should be used in order to maintain the required voltage at the host edge card connector. It is recommended that the 22 uF capacitors each have an equivalent series resistance of 0.22 Ω. The specification of the host power supply filtering network is beyond the scope of this specification, particularly because of the wide range of QSFP56 module Power Classes.





CL-QSFP56-LR4-200G
200G QSFP56 Optical Transceiver Module 2km
RoHS 6 compliant

Mechanical Diagram



-200Notice:

Carelink reserves the right to make changes or discontinue any optical link product or service identified in this publication, without notice, in order to improve design and/or performance.

Applications that are described herein for any of the optical link products are for illustrative purposes only. Carelink makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.